



AMV8 / CFM Chart

✓ = switch "ON"
 Blank = switch "OFF"

DIP SWITCH SETTINGS

		8	7	6	5	4	3	2	1
AMV80703BXA	TON								
	1.5			✓	✓				
	2.0		✓	✓	✓				✓
	2.5		✓	✓	✓	✓		✓	
	3.0		✓	✓	✓			✓	
	3.5		✓	✓	✓			✓	✓
AMV80905CXA	TON								
	2.0			✓	✓				
	2.5		✓	✓	✓	✓			✓
	3.0		✓	✓	✓				✓
	3.5		✓	✓	✓			✓	
	4.0		✓	✓	✓		✓	✓	
	5.0		✓	✓	✓			✓	✓
AMV81155CXA	TON								
	3.0		✓	✓	✓				✓
	3.5		✓	✓	✓			✓	
	4.0		✓	✓	✓		✓	✓	
	5.0		✓	✓	✓			✓	✓

► Cooling settings are nominal 400 cfm per ton.